

## 6.8 Spare Parts

Name	Order No.
FUM 230 function module Module fuse FF 4A (super quick) Replacement part: F 2,5A (quick) IEC 60127-2/I IEN 60127-2/I	6DP 1230-8CC Part No. GWE: 000000209528 Part No. GWE: 000000583096

## 6.9 Connector Pin Assignments of the X5 Backplane Connector

Z02	L+	B02	M (0 V)	D02	L+B2	F02	----
Z04	L+	B04	L+M	D04	L+B1	F04	----
Z06	IE1-	B06	IE2+	D06	IE2-	F06	IE1+
Z08	IE3-	B08	IE4+	D08	IE4-	F08	IE3+
Z10	IE5-	B10	IE6+	D10	IE6-	F10	IE5+
Z12	IE7-	B12	IE8+	D12	IE8-	F12	IE7+
Z14	IE9-	B14	IE10+	D14	IE10-	F14	IE9+
Z16	IE11-	B16	IE12+	D16	IE12-	F16	IE11+
Z18	IE13-	B18	IE14+	D18	IE14-	F18	IE13+
Z20	IE15-	B20	IE16+	D20	IE16-	F20	IE15+
Z22	COD1	B22	COD2*	D22	COD3*	F22	----
Z24	GV2	B24	GV3	D24	GV4	F24	GV1
Z26	GV6	B26	GV7	D26	GV8	F26	GV5
Z28	GV10	B28	GV11	D28	GV12	F28	GV9
Z30	GV14	B30	GV15	D30	GV16	F30	GV13
Z32	----	B32	M(0V)	D32	----	F32	----

The COD2 and COD 3 signals are only required when the 6DP 1230--8CC module replaces an older module of -8AA or -8BB type in an existing plant cabling. Then the module is compatible and the cabling has not to be changed.